

BS 18 LTX BL Q I (602359650) Cordless Drill / Screwdriver

18V 2x5.2Ah Li-ion; Charger ASC 55 (220-240 V / -); metaBOX 145 L

Order no. 602359650

EAN 4061792187726



Product may differ from Image



- Brushless drill/screwdriver with maximum power for demanding applications
- Metabo Quick System: quick change of bit retainer and bits, for flexible working
- Selectable "impuls" mode for removal of stubborn screws and for spot-drilling on smooth surfaces
- Precision Stop: electronic torque control with increased precision for accurate and intricate working
- Variable speed, forward and reverse rotation and quick stop for versatile use in wood and metal
- Overload protection: protects the motor from overheating
- Spindle with hexagonal recess for screwdriver bits for working without chuck
- Electronic safety shutdown: no kickback if the drill bit stops unexpectedly - for high user safety
- Integrated LED work light with night light function for optimal brightness in the work area
- Handy belt hook and bit holder can be fixed either on the right or left side
- Can be combined with all 18V battery packs and chargers of the CAS brands: www.cordless-alliance-system.com

Technical data

Characteristics

Type of battery pack	Li-ion
Battery voltage	18 V
Battery pack capacity	2 x 5.2 Ah
Maximum torque - soft	65 Nm / 575 ft. lbs
Pulse torque	65 Nm / 575 in-lbs
Maximum torque, hard	130 Nm / 1151 ft. lbs
Adjustable torque	1 - 20 Nm // 9 - 177 in-lbs
Drill Ø steel	13 mm / 1/2 "
Drill-Ø soft wood	68 mm / 2.68 "
No-load speed	0 - 550 / 0 - 2000 rpm
Chuck capacity	1.5 - 13 mm // 1/16 - 1/2 "
Weight (including battery pack)	2.4 kg / 5.3 lbs

Vibration

Drilling in metal	2.2 m/s ²
Uncertainty of measurement K	1.5 m/s ²

Noise emission

Sound pressure level	76 dB(A)
Sound power level (LwA)	87 dB(A)
Uncertainty of measurement K	3 dB(A)

Scope of delivery

- Quick-change chuck
- Belt hook and bit case
- 2 Li-Power battery packs (18 V/5.2 Ah)
- Charger ASC 55 "AIR COOLED"
- metaBOX 145 L
- Quick-change bit holder
- Side handle